

Hobbywing 30A Quickrun WP-16BL30 Brushless Car ESC



HWQRWP16BL30

Rating: Not Rated Yet

Price

Sales price R599,00

[Ask a question about this product](#)

Manufacturer [Hobbywing](#)

Description

Best for 1:16 and 1:18 scale cars

External programming port is easily connected to the LED Program Card (purchase separately) when setting the ESC.

Proportional brake with 8 steps of maximum brake force adjustment and 8 steps of drag brake force adjustment

8 steps of acceleration (launch) adjustment from "soft" to "Very aggressive" to fit different kinds of models, tires and tracks

Multiple protections: Low voltage cut-off protection / Over-heating protection / Throttle signal loss protection / Motor lock-up protection

One-button (the "SET" button on the ESC) sets the ESC. All parameters easily reset to factory default settings

Compatible with optional Digital LED Program Card

SPECS

Don't Peak Current Resistance

30A/180A/0.002s

Motor Type Supported: Senseless Brushless Motor

Car Applicable: 1:16 and 1:18 On-road/Off-road/Buggy/Monster

With Input: 2S LiPo or 3 cell NiMH

1. On-road: 2435 brushless or smaller motor with the KV smaller than 800

2. Off-road/Buggy/Monster: 2435 brushless or smaller motor with the KV smaller than 6000

With Input: 3S LiPo or 3 cell NiMH

1. On-road: 2435 brushless or smaller motor with the KV smaller than 5500

2. Off-road/Buggy/Monster: 2435 brushless or smaller motor with the KV smaller than 3000

BECD Output: 5V/1A (Linear Mode)

Size: Weight: 30(L) x 25(W) x 16(H) / 28g

External Program Port: Not Available

No cooling fan

Reviews

There are yet no reviews for this product.