

Hobbywing QuicRun 1080 G2 80A Brushed 2-3S Crawler ESC



HW30120202

Rating: Not Rated Yet

Price

Sales price R1235,00

[Ask a question about this product](#)

Manufacturer [Hobbywing](#)

Description

Specially Designed for Crawlers

The First Real Car Mode

The direction of the motor is switchable in real time by using the ldr channel on the transmitter.

Push the trigger for "forward"

Push the trigger for "brake"

Push the trigger with the "reverse channel" on will give you "reverse"

Requires an open channel on the receiver!

This new feature will provide the user with a unique experience unlike any other.

Four Running Modes Available

Forward with brakes

Forward, reverse with brakes

Forward and reverse

Real car running mode

Real-Time Adjustment of drag brake force

Adjust the drag brake force in real time

With the Drag brake Force Signal connected to an open channel on the receiver.

Users can adjust the drag brake force on the fly without the need to connect the Programmer.

Requires open channel on receiver!

Temperature control upgrade

The New design reduces operating temperatures of the ESC by about 15 degrees improving reliability.

The ESC also has a fan mount to meet additional cooling needs.

BEC Upgrade

The BEC Upgrade includes maximum output to 6A and provides 5V/7.4V/8.4V output options to support most of the servos on the market.

Multiple, easy to set parameters

15 Programmable Items let's drivers easily tune their vehicle with the LED Programming Box connected to the programming port.

IP67 Protection

IP67 Standard for being waterproof and dust proof for various weather conditions, and driving surfaces.

Note: The IP67 protection level mentioned above is splash-resistant, water-resistant and dust-resistant under normal use, and is tested under controlled laboratory conditions. Its effect is in the GB/T 4208-2017 (domestic) / IEC 60529 (overseas) standard to IP67 level. Splash, water and dust resistance are not guaranteed, and the level of protection may decline due to aging. Do not soak for a long time to avoid damaging the product.

LED Program Box Support

A standard General Hobbywing LED program box allows users to program the WP-Crawler-Brushed easily, (not included)

IP67

Waterproof

Peak Current: 80A/400A

Input Voltage: 2-3S LiPo/Li-I Cell NIMH

BEC Output: Switch Mode 5V/7.4V/8.4V @4A/6A Peak

Size: 37.2x31.8x18.8mm

Weight: 20.2g (w/Wire)

TV Rating Count

Standard 50 Size Brushed Motor

Red Wire Red 14AWG-200mm 1 / Black 14AWG-200mm 1

Output Wire Blue 14AWG-200mm 1 / Yellow 14AWG-200mm 1

Output Connectors XT60

Output Connectors 4.0mm Bullet Connectors (Female)

(Note: All the wire length above is the original length not the length you see from the outside.)

Reviews

There are yet no reviews for this product.